

1/2 HP AC BELT DRIVE WIFI® Garage Door Opener DEPENDABLE PERFORMANCE



KEY FEATURES

- QUIET OPERATION
Belt Drive
- WI-FI
Built In

INCLUDED ACCESSORIES:

3-Button Remote Control
Operates up to 3 openers or MyQ Light Accessories.



2220178

893 RGX

Multi-Function Control Panel
Includes lockout controls and accessory programmability.



6080979

882RGDW

POWERFUL ADD-ONS:

Mini Universal Remote Control
Compact and portable to provide quick, easy garage access..



2220185

374UT

Remote Light Control
Plug in any lamp to this device to control it with a smartphone or garage remote.



2220174

825LM

Remote Light Switch
Replaces an existing wall switch to control home lighting with a smartphone or garage remote.



2220183

823LM

Garage Door and Gate Monitor
Monitors and closes up to 4 garage doors from any room in the house.



2220175

829LM

RELIABLE

1/2 HP AC MOTOR IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

BELT DRIVE SYSTEM FOR QUIET, MAINTENANCE-FREE PERFORMANCE.

WARRANTY 4-YEAR MOTOR, 1-YEAR PARTS.

SMART

BUILT-IN WIFI FOR THE EASIEST WAY TO CONNECT THE GARAGE.

MYQ MOBILE APP LETS USERS RECEIVE ALERTS AND CONTROL THE OPENER FROM ANYWHERE.

SECURE

SECURITY+ 2.0® SENDS A NEW CODE WITH EVERY REMOTE CLICK.

POSILOCK® ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

ALERT-2-CLOSE SIGNALS WHEN A DOOR IS BEING CLOSED BY MyQ.

THE PROTECTOR SYSTEM® INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

MASTERFUL ENGINEERING.

MOTOR

- ½ Horsepower AC
- 1,625 RPM
- Automatic Thermal Protection
- Permanent Lubrication

POWER

- 120V AC
- 60 Hz Voltage
- 6A Current Rating
- UL Listed
- 4' Power Cord (3-Prong)

MECHANICS

- **Steel Chassis, T-Rail and Trolley**
- **Full Reinforced Belt Drive Mechanism** (16:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **Solid State Micro-controller** with Built-In Surge Suppressor (for Replacement Logic Boards, Order Part 050ACTWF)



DIMENSIONS

Rail Options	7'	8'	10'
Installed Length	124"	136"	160"
Max. Opening	7'6"	8'6"	10'6"

Headroom Clearance Required: 2"

7"
Per second for door to move upward

7"
Per second for door to move downward

STANDARD SPECS.

SECURITY

SECURITY+ 2.0®

RADIO CONTROLS

3-Button Remote Control (893 RGX)
Operating Range: **~200'**

Operating Temperature: -30°F to 150°F
Frequency:

- Remote Control: 310, 315 and 390 MHz Tri-Band
- Garage Door Opener: Frequency Agile on 310, 315, 390 MHz
- Security+ 2.0 Anti-Burglary Coding

SECURITY +2.0 ENCRYPTED CONTROLS

- Multi-Function Control Panel® (882RGDW)
- Program Remote Controls
 - Maintenance Alert System
 - Easy WiFi Setup

SMART

MyQ® RADIO

902-928 MHz
50-Channel FHSS

(Frequency Hopping Spread Spectrum)

- Provides 2-way communication from garage door opener and MyQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER*)

*May require an external adapter depending on the model and year of your vehicle. Visit HomeLink.com for additional information.

ELECTRICAL

LIGHTING



- Max. 1 100-Watt Light Bulb
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

SHIPPING.

SHIPPING WEIGHT (in lbs.)

CARTONS (2)



CARTON 1: 20" x 12" x 10"

- Multi-Function Control Panel (882RGDW)
- 3-Button Remote Control (893RGX)
- Garage Door Opener Head (8155WRGD)
- The Protector System® Safety Reversing Sensors

CARTON 2: 10"4" x 5" x 5" (for 7' Rail)

- Assembled Solid-Steel Chain T-Rail

CONVENIENCE AND SAFETY.

- Alert-2-Close/Unattended Close Operation†
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Up Safety Stop
- Safety Beam Obstruction Turns Lights On
- Maintenance Alert System
- Garage Door Opener Capacity of up to 12 Remote Controls, 1 Keyless Entry System and 16 MyQ Devices



HomeLink® and the HomeLink House® logo are registered trademarks of Gentex Corporation

†: To reduce the risk of injury to persons, only use alert-2-Close/Unattended Close Operation features when installed with a sectional door.